# When precision matters...

TW7972 Dimensions (mm)



The TW7972 is precision tuned triple band, *Accutenna*<sup>®</sup> technology antenna for reception of GPS L1/L2/L5, GLONASS G1/G2/G3, BeiDou B1/B2, Galileo E1/E5a+b plus L-band corrections signals. The TW7972 provides superior multi-path rejection and axial ratio, a linear phase response, and tight Phase Centre Variation (PCV), while protecting against intermodulation and saturation caused by high level cellular 700MHz signals. This antenna is ideal for precision agriculture, autonomous vehicle tracking and guidance, and other applications where precision matters.

Architecturally, the TW7972 features a dual feed circular stacked patch element. The signals from the two orthogonal feeds are summed in quadrature, pre-filtered in a low loss filter to protect against a wide range of potentially interfering signals, amplified in high linearity, wide-band LNA, then band-split, tightly filtered and amplified prior to signal recombination at the output.

The TW7972 provides reception for signals in the bands 1164MHz to 1254MHz and 1525MHz to 1606MHz. It is housed in a magnetic mount, weather-proof enclosure.

This product is also available in an OEM format (TW3967 for 28dB and TW3972E for 35dB)

# 

# Applications

Tallysman

**GNSS** 

- Precision GPS position
- Triple Frequency RTK systems (base and rovers)
- Positive Train Control (PTC) systems
- Military & Security

## Features

- Very low Noise, Pre-filtered Preamp, 2.5dB
- Axial ratio: <2dB typ.
- Tight Phase Center Variation
- LNA Gain 32 dB typ.
- Low current: 24mA typ.
- ESD circuit protection: 15 KV
- Invariant performance from: +2.5 to 16VDC

# Benefits

- Ideal for triple band RTK systems
- Great multipath rejection
- Increased system accuracy
- Great signal to noise ratio
- IP69K, REACH, and RoHS compliant



# When precision matters...

# TW7972 Triple Band GNSS Antenna + L-band Correction Services

**Specifications** (Measured a Vcc = 3V, and Temperature=25°C)

# Antenna

Patch Architecture		Circular, Dual Feed,	Circular, Dual Feed, Dual Stacked Patch		
E5a/L5 Gain (100mm ground plane)		-1.5dBic Min at Zen	-1.5dBic Min at Zenith		
E5b/G3 Gain (100mm ground plane)		2.5 dBic Min at Zeni	2.5 dBic Min at Zenith		
L2 Gain (100mm ground plane)		4.0 dBic Min at Zeni	4.0 dBic Min at Zenith		
G2 Gain (100mm ground plane)		2.5 dBic Min at Zeni	2.5 dBic Min at Zenith		
E1 Gain (100mm ground plane)		4.0 dBic Min at Zeni	4.0 dBic Min at Zenith		
L1 Gain (100mm ground plane)		4.0 dBic Min at Zeni	4.0 dBic Min at Zenith		
G1 Gain (100mm ground plane)		3.0 dBic Min at Zeni	3.0 dBic Min at Zenith		
Typical Axial Ratio @ zenith					
L5/E5ab	<2dB	L2/B2	<1.5dB		
G2	<2dB	L-Band	<1dB		
L1/E1	<1dB	G1	<1.5dB		

### **Electrical**

Bandwidth	L2/L5: 1164M	1164MHz-1254MHz (Filter bandwidth) L-band/L1: 1525 MHz-1606MHz (Filter bandwidth)				
Overall LNA Gain		32dB typ,				
Gain Variation with Temperature.		3dB max over operation	3dB max over operational temperature range			
LNA Noise Figure			2.5dB typ at 25°C			
VSWR (at LNA output)			<1.5:1 typ. 1.8:1 max.	<1.5:1 typ. 1.8:1 max.		
Supply Voltage Range	inge		+2.5 to 16VDC nomina	+2.5 to 16VDC nominal, up to 50mV p-p ripple		
EMI Immunity	Immunity		50V/Meter, excepting	50V/Meter, excepting L1+/-100MHz and L2 +/- 100MHz		
Supply Current			24mA typ. at 25°C, 25r	nA max at 75°C.		
ESD Circuit protection			15 KV air discharge.			
Out-of-Band Rejection	L5/E5	5/L2/G2	L1/E1/B1/G1			
	<1050 MHz	>45 dB	<1450 MHz >30	)dB		
	<1125 MHz	>30 dB	>1690 MHz > 30	0dB		
	>1350 MHz	>35 dB	>1730 MHz > 40	0dB		
Mechanicals & Env	vironmental					

### Mechanicals & Environmental

69mm (dia) x 22mm (H)
-40°C to +85°C
Radome: EXL9330, Base: Zamak White Metal
180 g
Magnetic Mount. Four-threaded holes (#6x32, 4mm deep in the base allow for screw mounting.
IP69K, RoHS, RED, and REACH compliant
Vertical axis: 50 G, other axes: 30 G
MIL STD 810D

### **Ordering Information**

TW7972 – Triple Band GNSS antenna with L-Band Correction 33-7972-xx-yyyy Where xx = connector type and yyyy = cable length in mm (where applicable)

Please refer to the Ordering Guide (http://www.tallysman.com/index.php/gnss/ordering-guide/) for the current and complete list of available connectors.



### 36 Steacie Drive Ottawa ON K2K 2A9 Canada

sales@tallysman.com Tel +1 613 591 3131 Fax 613 591 3121

The information provided herein is intended as a guide only and is subject to change without notice. This document is not to be regarded as a guarantee of performance. Tallysman Wireless Inc. hereby disclaims any or all warranties and liabilities of any kind. © 2015 Tallysman Wireless Inc. All rights reserved. v1.8